

This application note is applicable to the following members of the **D1U54P-W1500-12-HxxTC Series**:

Model Number Number	MPS #	Address	Standby Output	Airflow
D1U54P-W-1500-12-HC4TC	M1891	ADDR_SEL (External resistor)	3.3Vdc	Back to Front
D1U54P-W-1500-12-HA4TC	M1893		5Vdc	
D1U54P-W-1500-12-HB4TC	M1895		12Vdc	
D1U54P-W-1500-12-HC3TC	M1892		3.3Vdc	Front to Back
D1U54P-W-1500-12-HA3TC	M1894		5Vdc	

## Standard PMBus™

All data communicated over the PMBus™ interface uses PEC (Packet Error Checking) as defined by the standard for PMBus™ Power Systems Management Protocol Part 1 – General Requirements Rev 1.1. To avoid setting CML errors when issuing “write” PEC protocol must be followed and therefore strongly recommended to fully utilize the PEC byte to validate all transactions and to repeat if not validated.

Linear data formatting is used for all passed parameters. Block reads (where the loose byte received denotes the remaining byte to be clocked out) are not supported on this product series.

A minimum of 300µs delay between transactions (between the STOP of one command and the START of the next command) is recommended for robust communications.

Note: 100KHz I²C communications is supported for the PMBus™ interface.

Note: The PMBus™ slave controller does “clock stretch” on ACK or NAK.

## Device Details

Power Supply Controllers			
Vendor	MFG Part Number	Package	Description
Microchip Technology Inc.	DSPIC33FJ64GS606T-50I/PT	TQFP64	( Secondary) IC Dig SMT Microcontroller PIC33 TQFP64 64k 9kB 50MHz
Microchip Technology Inc.	DSPIC33FJ16GS504T-50I/PT	TQFP44	( Primary) IC Dig SMT Controller PWM Industrial PIC33 TQFP44 40MHz

Power Supply External EEPROM			
Vendor	MFG Part Number	Package	Description
Microchip Technology Inc.	24AA024T-I/MS	MSOP8	IC Dig SMT EEPROM CMOS Serial I2C AT24CXX MSOP8 2kB

## Device Addressing Methods

(See **D1U54P-12-CONC Interface Card; Application Note ACAN-64 for Additional Details**):

There are two methods whereby the three lower order address bits of the seven bit address structure of the internal addressable devices can be assigned (for the secondary microcontroller and the EEPROM device A0, A1 & A2; see the PMBus™ standard). These are as follows:

1. Using the ADDR signal pin (Pin# A3) in digital mode by either:
    - a. Un-terminating (leaving open circuit); this will set a default setting of “111” for the last three addressable bits (A0, A1 & A2) of the seven bit address byte.
    - b. Terminating the pin to RTN/ground (Pin numbers A2/B2); this method will set a default address of “000” for the last three addressable bits (A0, A1 & A2) of the address byte.
  2. Using the ADDR signal pin (Pin# A3) in analogue mode by connection of an external resistance to RTN/ground (pin numbers A2/B2).
- For the possible external resistance values this will result in the following address combinations:

HEX Address Combinations by Analogue Method; ADDR External Resistance Values		
ADDR External Resistance to RTN/Ground (KΩ; ±5% Tolerance)	Power Module Secondary Main Controller (Serial Slave Address)*	Power Module EEPROM (Serial Slave Address)*
0.82	0xB0	0xA0
2.7	0xB2	0xA2
5.6	0xB4	0xA4
8.2	0xB6	0xA6
15	0xB8	0xA8
27	0xBA	0xAA
56	0xBC	0xAC
180	0xBE	0xAE

\*The D1U54P-W-1500-12-HxxTC uses 7-bit left shifted” device addressing; the EEPROM addressing follows a similar convention (commences at base address 0xA0); the lowest order bit of the address is the Read/Write bit. It is assumed that the Read Write bit is set to logic “0” (for addresses shown in the table above).

**PMBus™ Commands**

Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition	Supported ?
00	PAGE	R/W	All	1			Command to provide ability to configure, control & monitor multiple outputs	YES
01	OPERATION See Table at rear of Document Link: <a href="#">Operation_Data_01</a>	R/W	All	1	5:0		Set output margin high/low voltages	NO
01	ON_OFF_CONFIG See table at rear of Document Link: <a href="#">ON_OFF_Data_02</a>	R	All	1	7:6		Turn the unit on/off in conjunction with digital input from PSON_H	YES
02	CLEAR_FAULTS	W	All	1	0	ON_OFF_DELAY	Set when Turn off immediately (default) / 0 = Use delay @ turn-off	YES
02	CLEAR_FAULTS	W	All	1	1	ON_OFF_POLARITY	Set when Power on processing is active high (default)	YES
02	CLEAR_FAULTS	W	All	1	2	USE_CONTROL	Set when Use CONTROL pin for on/off power processing (default)	YES
02	CLEAR_FAULTS	W	All	1	3	USE_OPERATION	Set when Use OPERATION command for on/off power processing (default)	YES
02	CLEAR_FAULTS	W	All	1	4	USE_CNTL_AND_OP	Set when Use both CONTROL pin & OPERATION command (default)	YES
02	CLEAR_FAULTS	W	All	1	5	RESERVED		NO
02	CLEAR_FAULTS	W	All	1	6	RESERVED		NO
02	CLEAR_FAULTS	W	All	1	7	RESERVED		NO
03	WRITE_PROTECT	R/W	All	1			Write only command clears all faults that have been set in all the STATUS_XXXX registers simultaneously	YES
10	VOUT_COMMAND	R	0	1			Disable all writes except: WRITE_PROTECT	
10	VOUT_COMMAND	R	1	1			Disable all writes except: WRITE_PROTECT, OPERATION, PAGE	
10	VOUT_COMMAND	R	1	1			Disable all writes except: WRITE_PROTECT, OPERATION, PAGE, ON_OFF_CONFIG, VOUT_COMMAND	
10	VOUT_COMMAND	R	1	1			Enable all writes	YES
19	CAPABILITY	R	All	1	0:3	RESERVED		NO
19	CAPABILITY	R	All	1	4	SMBALERT_L	Set when device has SMBALERT_L pin which supports the SMBus Alert Response protocol	YES
19	CAPABILITY	R	All	1	6:5	MAX_BUS_SPEED	01 = Max supported bus speed = 400kHz; 00 Max supported bus speed = 100kHz	YES
19	CAPABILITY	R	All	1	7	PEC	Set when packet error checking is supported	YES
20	VOUT_MODE	R	0	1			Single data byte sets the READ_VOUT sensor to linear mode data format and supplies N exponent for translation to volts	
20	VOUT_MODE	R	0	1			PMBus Spec - Part II - Revision 1.1 - Sections 8.1-8.3	
20	VSTBY_MODE	R	1	1			Single data byte sets the READ_VSTBY sensor to linear mode data format and supplies N exponent for translation to volts	
20	VSTBY_MODE	R	1	1			PMBus Spec - Part II - Revision 1.1 - Sections 8.1-8.3	
21	VOUT_COMMAND	R/W	All	2				YES
25	VOUT_MARGIN_HIGH	R/W	0	2			Load the unit with the voltage to which the output is to be changed when the OPERATION command set to "Margin High"	NO
25	VSTBY_MARGIN_LOW	R/W	1	2			Load the unit with the voltage to which the output is to be changed when the OPERATION command set to "Margin High"	NO
26	VOUT_MARGIN_HIGH	R/W	0	2			Load the unit with the voltage to which the output is to be changed when the OPERATION command set to "Margin Low"	NO
26	VSTBY_MARGIN_LOW	R/W	1	2			Load the unit with the voltage to which the output is to be changed when the OPERATION command set to "Margin Low"	NO
3A	FAN_CONFIG_1_2	R	All	1	0	FAN_2_TACH_PULSES	Fan 2 Tachometer pulses per revolution (lower bit)	NO
3A	FAN_CONFIG_1_2	R	All	1	1	FAN_2_TACH_PULSES	Fan 2 Tachometer pulses per revolution (upper bit)	NO
3A	FAN_CONFIG_1_2	R	All	1	2	FAN_2_SETTING_MODE	Set when fan is commanded in RPM (Clear when fan is commanded in Duty Cycle)	NO
3A	FAN_CONFIG_1_2	R	All	1	3	FAN_2_INSTALLATION	Set when fan is installed in position 2	NO
3A	FAN_CONFIG_1_2	R	All	1	4	FAN_1_TACH_PULSES	Fan 1 Tachometer pulses per revolution (lower bit)	YES
3A	FAN_CONFIG_1_2	R	All	1	5	FAN_1_TACH_PULSES	Fan 1 Tachometer pulses per revolution (upper bit)	YES
3A	FAN_CONFIG_1_2	R	All	1	6	FAN_1_SETTING_MODE	Set when fan is commanded in RPM (Clear when fan is commanded in Duty Cycle)	YES
3A	FAN_CONFIG_1_2	R	All	1	7	FAN_1_INSTALLATION	Set when fan is installed in position 1	YES

Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition	Supported?
3B	FAN_COMMAND_1	R/W	All	2		Link to Manual Fan Control notes: <a href="#">Commands_3B_note</a>	Manual fan override command fan speed value in Duty Cycle Command speed formatted in Linear as per command 0x90 - READ_FAN_SPEED_1	<b>YES</b>
3C	FAN_COMMAND_2	R/W	All	2			Manual fan override command fan speed value in Duty Cycle Command speed formatted in Linear as per command 0x91 - READ_FAN_SPEED_2	
40	VOUT_OV_FAULT_LIMIT	R	0	2		Links to Returned Response: <a href="#">HA3TC,HA4TC</a> <a href="#">HC3TC,HC4TC</a> <a href="#">HB4TC</a>	Main Output Ovvoltage Fault Limit	<b>YES</b>
40	VSTBY_OV_FAULT_LIMIT	R	1	2			Standby(Auxiliary) Output Ovvoltage Fault Limit	<b>YES</b>
41	VOUT_OV_FAULT_RESPONSE	R	0	1			Main Output Ovvoltage Fault Response Actions	<b>YES</b>
41	VSTBY_OV_FAULT_RESPONSE	R	1	1			Standby(Auxiliary) Output Ovvoltage Fault Response Actions	<b>YES</b>
42	VOUT_OV_WARN_LIMIT	R	0	2			Main Output Ovvoltage Warning Limit	<b>YES</b>
42	VSTBY_OV_WARN_LIMIT	R	1	2			Standby(Auxiliary) Output Ovvoltage Warning Limit	<b>YES</b>
43	VOUT_UV_WARN_LIMIT	R	0	2			Main Output Undervoltage Warning Limit	<b>YES</b>
43	VSTBY_UV_WARN_LIMIT	R	1	2			Standby(Auxiliary) Output Undervoltage Warning Limit	<b>YES</b>
44	VOUT_UV_FAULT_LIMIT	R	0	2			Main Output Undervoltage Fault Limit	<b>YES</b>
44	VSTBY_UV_FAULT_LIMIT	R	1	2			Standby(Auxiliary) Output Undervoltage Fault Limit	<b>YES</b>
45	VOUT_UV_FAULT_RESPONSE	R	0	1			Main Output Undervoltage Fault Response Actions	<b>YES</b>
45	VSTBY_UV_FAULT_RESPONSE	R	1	1			Standby(Auxiliary) Output Undervoltage Fault Response Actions	<b>YES</b>
46	IOUT_OC_FAULT_LIMIT	R	0	2			Main Output Overcurrent Fault Limit	<b>YES</b>
46	ISTBY_OC_FAULT_LIMIT	R	1	2			Standby(Auxiliary) Output Overvoltage Fault Limit	<b>YES</b>
47	IOUT_OC_FAULT_RESPONSE	R	0	1			Main Output Overcurrent Fault Response Actions	<b>YES</b>
47	ISTBY_OC_FAULT_RESPONSE	R	1	1			Standby(Auxiliary) Output Overcurrent Fault Response Actions	<b>YES</b>
4A	IOUT_OC_WARN_LIMIT	R	0	2			Main Output Overcurrent Warning Limit	<b>YES</b>
4A	ISTBY_OC_WARN_LIMIT	R	1	2			Standby(Auxiliary) Output Overvoltage Warning Limit	<b>YES</b>
4F	AIRFLOW_1_OT_FAULT_LIMIT	R	0	2		Airflow 1 Overttemperature Fault Limit Airflow 2 Overttemperature Fault Limit Hotspot 1 Overttemperature Fault Limit Hotspot 2 Overttemperature Fault Limit Hotspot 3 Overttemperature Fault Limit Airflow 1 Overttemperature Fault Response Actions Airflow 2 Overttemperature Fault Response Actions Hotspot 1 Overttemperature Fault Response Actions Hotspot 2 Overttemperature Fault Response Actions Hotspot 3 Overttemperature Fault Response Actions Airflow 1 Overttemperature Warning Limit Airflow 2 Overttemperature Warning Limit Hotspot 1 Overttemperature Warning Limit Hotspot 2 Overttemperature Warning Limit Hotspot 3 Overttemperature Warning Limit Input Ovvoltage Fault Limit Input Ovvoltage Fault Response Actions Input Ovvoltage Warning Limit Input Undervoltage Warning Limit Input Undervoltage Fault Limit Input Undervoltage Fault Response Actions Input Overcurrent Fault Limit Input Overcurrent Fault Response Actions Input Overcurrent Warning Limit Power Good On Main Output Voltage Limit Power Good Off Main Output Voltage Limit Output Overpower Fault Limit Output Overpower Fault Response Actions	Airflow 1 Overttemperature Fault Limit	<b>YES</b>
4F	AIRFLOW_2_OT_FAULT_LIMIT	R	1	2			Airflow 2 Overttemperature Fault Limit	<b>YES</b>
4F	HOTSPOT_1_OT_FAULT_LIMIT	R	2	2			Hotspot 1 Overttemperature Fault Limit	<b>YES</b>
4F	HOTSPOT_2_OT_FAULT_LIMIT	R	3	2			Hotspot 2 Overttemperature Fault Limit	<b>YES</b>
4F	HOTSPOT_3_OT_FAULT_LIMIT	R	4	2			Hotspot 3 Overttemperature Fault Limit	<b>YES</b>
50	AIRFLOW_1_OT_FAULT_RESPONSE	R	0	1			Airflow 1 Overttemperature Fault Response Actions	<b>YES</b>
50	AIRFLOW_2_OT_FAULT_RESPONSE	R	1	1			Airflow 2 Overttemperature Fault Response Actions	<b>YES</b>
50	HOTSPOT_1_OT_FAULT_RESPONSE	R	2	1			Hotspot 1 Overttemperature Fault Response Actions	<b>YES</b>
50	HOTSPOT_2_OT_FAULT_RESPONSE	R	3	1			Hotspot 2 Overttemperature Fault Response Actions	<b>YES</b>
50	HOTSPOT_3_OT_FAULT_RESPONSE	R	4	1			Hotspot 3 Overttemperature Fault Response Actions	<b>YES</b>
51	AIRFLOW_1_OT_WARN_LIMIT	R	0	2			Airflow 1 Overttemperature Warning Limit	<b>YES</b>
51	AIRFLOW_2_OT_WARN_LIMIT	R	1	2			Airflow 2 Overttemperature Warning Limit	<b>YES</b>
51	HOTSPOT_1_OT_WARN_LIMIT	R	2	2			Hotspot 1 Overttemperature Warning Limit	<b>YES</b>
51	HOTSPOT_2_OT_WARN_LIMIT	R	3	2			Hotspot 2 Overttemperature Warning Limit	<b>YES</b>
51	HOTSPOT_3_OT_WARN_LIMIT	R	4	2			Hotspot 3 Overttemperature Warning Limit	<b>YES</b>
55	VIN_OV_FAULT_LIMIT	R	0	2			Input Ovvoltage Fault Limit	<b>YES</b>
56	VIN_OV_FAULT_RESPONSE	R	0	1			Input Ovvoltage Fault Response Actions	<b>YES</b>
57	VIN_OV_WARN_LIMIT	R	0	2			Input Ovvoltage Warning Limit	<b>YES</b>
58	VIN_UV_WARN_LIMIT	R	0	2			Input Undervoltage Warning Limit	<b>YES</b>
59	VIN_UV_FAULT_LIMIT	R	0	2			Input Undervoltage Fault Limit	<b>YES</b>
5A	VIN_UV_FAULT_RESPONSE	R	0	1			Input Undervoltage Fault Response Actions	<b>YES</b>
5B	IIN_OC_FAULT_LIMIT	R	0	2			Input Overcurrent Fault Limit	<b>YES</b>
5C	IIN_OC_FAULT_RESPONSE	R	0	1			Input Overcurrent Fault Response Actions	<b>YES</b>
5D	IIN_OC_WARN_LIMIT	R	0	2			Input Overcurrent Warning Limit	<b>YES</b>
5E	POWER_GOOD_ON	R	0	2			Power Good On Main Output Voltage Limit	<b>YES</b>
5F	POWER_GOOD_OFF	R	0	2			Power Good Off Main Output Voltage Limit	<b>YES</b>
68	POUT_OP_FAULT_LIMIT	R	0	2			Output Overpower Fault Limit	<b>YES</b>
69	POUT_OP_FAULT_RESPONSE	R	0	1			Output Overpower Fault Response Actions	<b>YES</b>

6A	POUT_OP_WARN_LIMIT	R	0	2			Output Overpower Warning Limit	YES
6B	PIN_OP_WARN_LIMIT	R	0	2			Input Overpower Warning Limit	YES
Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition	Supported?
79	STATUS_BYTE	R	All	1	0	NONE_F_W	Set when a fault not listed in [7:1] occurred	NO
					1	CML_F	Set when a communications, memory, or logic fault has occurred	YES
					2	TEMPERATURE_F_W	Set when an overtemperature fault or warning has occurred	YES
					3	INPUT_UV_F	Set when an input undervoltage fault has occurred	YES
					4	OUTPUT_OC_F	Set when an output overcurrent fault has occurred	YES
					5	OUTPUT_OV_F	Set when an output overvoltage fault has occurred	YES
					6	UNIT_OFF	Set when unit not providing power to the output	YES
					7	BUSY_F	Asserted when device busy and unable to respond fault	YES
79	STATUS_WORD	R	All	2	0	NONE_F_W	Set when a fault not listed in [7:1] occurred	NO
					1	CML_F	Set when a communications, memory, or logic fault has occurred	YES
					2	TEMPERATURE_F_W	Set when an overtemperature fault or warning has occurred	YES
					3	INPUT_UV_F	Set when an input undervoltage fault has occurred	YES
					4	OUTPUT_OC_F	Set when an output overcurrent fault has occurred	YES
					5	OUTPUT_OV_F	Set when an output overvoltage fault has occurred	YES
					6	UNIT_OFF	Set when unit not providing power to the output	YES
					7	BUSY_F	Asserted when device busy and unable to respond fault	YES
					8	UNKNOWN_F_W	Set when a fault not listed in [15:1] has occurred	NO
					9	STATUS_OTHER_F_W	Set when a bit in command STATUS_OTHER set	NO
					10	FANS_F_W	Set when a fan fault or warning has occurred	YES
					11	POWER_GOOD_L	Set when the POWER_GOOD signal is negated	YES
					12	MFR_SPECIFIC_F_W	Manufacturer specific fault or warning has occurred	YES
					13	INPUT_F_W	Set when an Input voltage/current/power fault or warning has occurred	YES
					14	IOUT_POUT_F_W	Set when an output current / output power fault or warning has occurred	YES
					15	VOUT_F_W	Set when an output voltage fault or warning has occurred	YES
7A	STATUS_VOUT	R	0	1	0	VOUT_TRACKING_E	Set when an error in the output voltage during power-up/down has occurred	NO
					1	TON_MAX_W	Set when the output turn-on timing has exceeded the TON_MAX warning timing	NO
					2	TON_MAX_F	Set when the output turn-on timing has exceeded the TON_MAX fault timing	NO
					3	VOUT_MAX_F	Set when the output is set higher than the commanded VOUT_MAX limit	NO
					4	VOUT_UV_F	Set when an output undervoltage fault has occurred	YES
					5	VOUT_UV_W	Set when an output undervoltage warning has occurred	YES
					6	VOUT_OV_W	Set when an output overvoltage warning has occurred	YES
					7	VOUT_OV_F	Set when an output overvoltage fault has occurred	YES
7A	STATUS_VSTBY	R	1	1	0	VOUT_TRACKING_E	Set when an error in the output voltage during power-up/down has occurred	NO
					1	TON_MAX_W	Set when the output turn-on timing has exceeded the TON_MAX warning timing	NO
					2	TON_MAX_F	Set when the output turn-on timing has exceeded the TON_MAX fault timing	NO
					3	VOUT_MAX_F	Set when the output is set higher than the commanded VOUT_MAX limit	NO
					4	VOUT_UV_F	Set when an output undervoltage fault has occurred	NO
					5	VOUT_UV_W	Set when an output undervoltage warning has occurred	YES
					6	VOUT_OV_W	Set when an output overvoltage warning has occurred	YES
					7	VOUT_OV_F	Set when an output overvoltage fault has occurred	YES

Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition	Supported?
7B	STATUS_IOUT	R	0	1	0	POUT_OP_W	Set when an output overpower warning has occurred	YES
					1	POUT_OP_F	Set when an output overpower fault has occurred	YES
					2	POWER_LIMIT_MODE	Set when the unit has entered output power limiting mode	NO
					3	CURRENT_SHARE_F	Set when an output current share fault has occurred	NO
					4	IOUT_UC_W	Set when an output undercurrent fault has occurred	NO
					5	IOUT_OC_W	Set when an output overcurrent warning has occurred	YES
					6	IOUT_OC_SHUTDOWN	Set when an output overcurrent and low voltage shutdown fault has occurred	YES
					7	IOUT_OC_F	Set when an output overcurrent fault has occurred	YES
7B	STATUS_ISTBY	R	1	1	0	POUT_OP_W	Set when an output overpower warning has occurred	YES
					1	POUT_OP_F	Set when an output overpower fault has occurred	YES
					2	POWER_LIMIT_MODE	Set when the unit has entered output power limiting mode	NO
					3	CURRENT_SHARE_F	Set when an output current share fault has occurred	NO
					4	IOUT_UC_W	Set when an output undercurrent fault has occurred	NO
					5	IOUT_OC_W	Set when an output overcurrent warning has occurred	YES
					6	IOUT_OC_SHUTDOWN	Set when an output overcurrent and low voltage shutdown fault has occurred	YES
					7	IOUT_OC_F	Set when an output overcurrent fault has occurred	YES
7C	STATUS_INPUT	R	All	1	0	PIN_OP_W	Set when an input overpower warning has occurred	YES
					1	IIN_OC_W	Set when an input overcurrent warning has occurred	YES
					2	IIN_OC_F	Set when an input overcurrent fault has occurred	YES
					3	VIN_UV_OFF	Set when the Unit is OFF for insufficient input voltage	YES
					4	VIN_UV_F	Set when an input undervoltage fault has occurred	YES
					5	VIN_UV_W	Set when an input undervoltage warning has occurred	YES
					6	VIN_OV_W	Set when an input overvoltage warning has occurred	YES
					7	VIN_OV_F	Set when an input overvoltage fault has occurred	YES
7D	STATUS_TEMPERATURE	R	All	1	0	RESERVED	Reserved	NO
					1	RESERVED	Reserved	NO
					2	RESERVED	Reserved	NO
					3	RESERVED	Reserved	NO
					4	TEMPERATURE_UT_F	Set when an undertemperature fault has occurred	NO
					5	TEMPERATURE_UT_W	Set when an undertemperature warning has occurred	NO
					6	TEMPERATURE_OT_W	Set when an overtemperature warning has occurred	YES
					7	TEMPERATURE_OT_F	Set when an overtemperature fault has occurred	YES
7E	STATUS_CML	R	All	1	0	OTHER_MEMORY_F	Set when another memory or logic fault has occurred	NO
					1	OTHER_COMM_F	Set when a communication fault not listed in [7:3] has occurred (example: UART or SPI)	YES
					2	RESERVED	Reserved	NO
					3	PROCESSOR_F	Set when a processor fault is detected	NO
					4	MEMORY_F	Set when a memory fault is detected (example: Checksum errors during bootload)	NO
					5	PEC_ERROR_F	Set when a packet error checking (PEC) failed has occurred	YES
					6	DATA_ERROR_F	Set when invalid or unsupported data is received	YES
					7	COMMAND_ERROR_F	Set when an invalid or unsupported command is received	YES
7F	STATUS_OTHER	R	All	1	0	RESERVED	Reserved	NO
					1	ORING_OUTPUT_F	Set when output ORing device fault occurs	NO
					2	ORING_INPUT_B_F	Set when input B ORing device fault occurs	NO
					3	ORING_INPUT_A_F	Set when input A ORing device fault occurs	NO
					4	FUSE_INPUT_B_F	Set when input B fuse/breaker fault occurs	NO
					5	FUSE_INPUT_A_F	Set when input A fuse/breaker fault occurs	NO
					6	RESERVED	Reserved	NO
					7	RESERVED	Reserved	NO

Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition	Supported?
80	STATUS_MFR_SPECIFIC	R	All	1	0	RESERVED	Reserved	NO
					1	RESERVED	Reserved	NO
					2	VINT_RANGE_W	Set when an internal voltage (VCC2, VCC4, or VDD) out-of-range warning has occurred	NO
					3	VINT_RANGE_F	Set when an internal voltage (VCC2, VCC4, or VDD) out-of-range fault has occurred	YES
					4	VBUS_UV_F	Set when the primary boost output bus undervoltage fault has occurred	YES
					5	VBUS_UV_W	Set when the primary boost output bus undervoltage warning has occurred	YES
					6	VBUS_OV_W	Set when the primary boost output bus overvoltage warning has occurred	YES
					7	VBUS_OV_F	Set when the primary boost output bus overvoltage fault has occurred	YES
81	STATUS_FANS_1_2	R	All	1	0	FAN_AIRFLOW_W	Airflow warning	NO
					1	FAN_AIRFLOW_F	Airflow fault	NO
					2	FAN_2_OVERRIDE	Fan 2 speed overridden	NO
					3	FAN_1_OVERRIDE	Fan 1 speed overridden	YES
					4	FAN_2_W	Fan 2 warning	NO
					5	FAN_1_W	Fan 1 warning	YES
					6	FAN_2_F	Fan 2 fault	NO
					7	FAN_1_F	Fan 1 fault	YES
82	STATUS_FANS_3_4	R	All	1	0	FAN_AIRFLOW_W	Airflow warning	NO
					1	FAN_AIRFLOW_F	Airflow fault	NO
					2	FAN_4_OVERRIDE	Fan 4 speed overridden	NO
					3	FAN_3_OVERRIDE	Fan 3 speed overridden	NO
					4	FAN_4_W	Fan 4 warning	NO
					5	FAN_3_W	Fan 3 warning	NO
					6	FAN_4_F	Fan 4 fault	NO
					7	FAN_3_F	Fan 3 fault	NO
88	READ_VIN	R	All	2	Link to Sensor Data: <a href="#">Sensor Data HA4TC</a> <a href="#">Sensor Data HA3TC</a> <a href="#">Sensor Data HB4TC</a> <a href="#">Sensor Data HC4TC</a> <a href="#">Sensor Data HC3TC</a>	Input Voltage Sensor Reading	YES	
89	READ_IIN	R	All	2		Input Current Sensor Reading	YES	
8B	READ_VOUT	R	0	2		Main Output Voltage Sensor Reading	YES	
8B	READ_VSTBY	R	1	2		Standby(Auxilliary) Output Voltage Sensor Reading	YES	
8C	READ_IOUT	R	0	2		Main Output Current Sensor Reading	YES	
8C	READ_ISSTBY	R	1	2		Standby(Auxilliary) Output Current Sensor Reading	YES	
8D	READ_TEMPERATURE_1	R	0	2		Airflow 1 Temperature Sensor Reading	YES	
8E	READ_TEMPERATURE_2	R	0	2		Airflow 2 Temperature Sensor Reading	YES	
8F	READ_TEMPERATURE_3	R	0	2		Hotspot 1 Temperature Sensor Reading	YES	
8F	READ_TEMPERATURE_3	R	1	2		Hotspot 2 Temperature Sensor Reading	YES	
8F	READ_TEMPERATURE_3	R	2	2		Hotspot 3 Temperature Sensor Reading	NO	
90	READ_FAN_SPEED_1	R	0	2		Fan 1 Speed Sensor Reading	YES	
91	READ_FAN_SPEED_2	R	0	2		Fan 2 Speed Sensor Reading	NO	
96	READ_POUT	R	All	2		Output Power Sensor Reading	YES	
97	READ_PIN	R	All	2		Input Power Sensor Reading	YES	
98	PMBUS_REVISION	R	All	1		PMBus Specification Revision	YES	

Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition	Supported?
99	MFR_ID	R	All	10		Link to Returned Results: <a href="#">Command_99</a>	Power Supply Company Name	<b>YES</b>
9A	MFR_MODEL	R/W	All	32 Max		Link to Returned Results: <a href="#">Command_9A</a>	Power Supply Model Number	<b>YES</b>
9B	MFR_REVISION	R	0	17		Link to Returned Results: <a href="#">MFR_REVISION_RTN</a>	Power Supply Firmware Revision	<b>YES</b>
9B	MFR_REVISION	R	1	17		Link to Returned Results: <a href="#">MFR_REVISION_RTN</a>	Power Supply Firmware Revision	<b>YES</b>
9B	MFR_REVISION	R	2	17		Link to Returned Results: <a href="#">MFR_REVISION_RTN</a>	Power Supply Firmware Revision	<b>NO</b>
9C	MFR_LOCATION	R/W	All	16 Max		Link to Returned Results: <a href="#">MFR_LOCATION_RTN</a>	Power Supply Manufacture Location	<b>YES</b>
9D	MFR_DATE	R/W	All	16 Max		Link to Returned Results: <a href="#">COMMAND_9D</a>	Power Supply Manufacture Date	<b>YES</b>
9E	MFR_SERIAL	R/W	All	16 Max		Link to Returned Results: <a href="#">COMMAND_9E</a>	Power Supply Serial Number	<b>YES</b>
A0	MFR_VIN_MIN	R	All	2		Link to Returned Results: <a href="#">Response_Parametric</a>	Power Supply Input Voltage Minimum Specification	<b>YES</b>
A1	MFR_VIN_MAX	R	All	2			Power Supply Input Voltage Maximum Specification	<b>YES</b>
A2	MFR_IIN_MAX	R	All	2			Power Supply Input Current Maximum Specification	<b>YES</b>
A3	MFR_PIN_MAX	R	All	2			Power Supply Input Power Maximum Specification	<b>YES</b>
A4	MFR_VOUT_MIN	R	All	2			Power Supply Main Output Voltage Minimum Specification	<b>YES</b>
A5	MFR_VOUT_MAX	R	All	2			Power Supply Main Output Voltage Maximum Specification	<b>YES</b>
A6	MFR_IOUT_MAX	R	All	2			Power Supply Main Output Current Maximum Specification	<b>YES</b>
A7	MFR_POUT_MAX	R	All	2			Power Supply Output Power Maximum Specification	<b>YES</b>
A8	MFR_TAMBIENT_MAX	R	All	2			Power Supply Operating Ambient Temperature Maximum Specification	<b>YES</b>
A9	MFR_TAMBIENT_MIN	R	All	2			Power Supply Operating Ambient Temperature Minimum Specification	<b>YES</b>
AA	MFR_EFFICIENCY_LL	R	All	2			Power Supply Low-Line Input Voltage Specification	<b>NO</b>
				2			Power Supply Low-Line Low Power Specification	<b>NO</b>
				2			Power Supply Low-Line Low Power Efficiency Specification	<b>NO</b>
				2			Power Supply Low-Line Medium Power Specification	<b>NO</b>
				2			Power Supply Low-Line Medium Power Efficiency Specification	<b>NO</b>
				2			Power Supply Low-Line High Power Specification	<b>NO</b>
				2			Power Supply Low-Line High Power Efficiency Specification	<b>NO</b>
AB	MFR_EFFICIENCY_HL	R	All	2			Power Supply High-Line Input Voltage Specification	<b>YES</b>
				2			Power Supply High-Line Low Power Specification	<b>YES</b>
				2			Power Supply High-Line Low Power Efficiency Specification	<b>YES</b>
				2			Power Supply High-Line Medium Power Specification	<b>YES</b>
				2			Power Supply High-Line Medium Power Efficiency Specification	<b>YES</b>
				2			Power Supply High-Line High Power Specification	<b>YES</b>
				2			Power Supply High-Line High Power Efficiency Specification	<b>YES</b>

Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition	Supported?
E0	PS_STATUS	R	All	2	0	CALIBRATION	Set when the unit is in Calibration mode	YES
					1	VSTBY_SELECT	Set when Vstby set to 5V; de-Set when Vstby set to 3.3V	YES
					2	PS_KILL	Set when the PS_KILL pin is defeated and the unit is properly seated in the chassis	YES
					3	VIN_OK	Set when the input voltage is within operating specification	YES
					4	VIN_RANGE	Set when input voltage range is high; de-Set when input voltage range is low	YES
					5	PFC_BUS	Set when the PFC BUS is within operating specification	YES
					6	PS_ON	Set when the PS_ON logic set to enable the main output	YES
					7	POWER_GOOD	Set when main output power delivered to unit is OK; mirrors the digital output signal	YES
					8	POWER_DOWN	Set when bootloader is taking control and the main output and PFC need to be shutdown	YES
					9	BOOTLOAD_COMPLETE	Set when the bootloader has completed and system reset needs to be Set	YES
					10	UNUSED		NO
					11	UNUSED		NO
					12	UNUSED		NO
					13	UNUSED		NO
					14	WARNING	Set when power supply warning has occurred; tracks 'WARNING' status LED	YES
					15	FAULT	Set when power supply fault has occurred; tracks 'FAULT' status LED	YES
E1	EEPROM_WP See Example Data: <a href="#">EEPROM_DATA_example</a>	R/W	All	1			Byte to enable (write 0x9A) or disable (write 0x56) writes to the external EEPROM	YES
E2	READ_HOURS_USED	R	All	3			Power Supply Accumulated Main Output Power-On Hours	YES
EE	PMBUS_CONFIG Link to: <a href="#">PMBUS_Configuration</a>	R	All	2	0	DATA_FORMAT	0 = Linear data format 1 = Direct data format	YES
					1	SMBALERT_L	0 = SMBALERT_L implemented & supported 1 = SMBALERT not implemented	NO
					2	MAX_BUS_SPEED	0 = 100kHz 1 = 400kHz	NO
					3	PEC	0 = PEC not supported 1 = PEC supported	YES
					4:7	RESERVED		NO
					8:1 5	CMD_KEY	Command activation/verification key = 0x5A	YES
EF	LED_CONTROL Link to LED Data: <a href="#">LED_Control</a>	R	All	1	0:2	LED_MODE	LED mode change bits	YES
					3:6	RESERVED		NO
					7	LED_CONTROL	LED manual/auto control toggle bit	NO
F0	READ_RESETS	R	All	2			RCON register status flags for troubleshooting	YES
							RCON2 register status flags for troubleshooting	
F8	BOOTLOAD_RESTART	R/W	All	1			Bootloader completion and application restart request command	YES
FA	BOOTLOAD_REQUEST	R/W	All	6			Bootloader request command	YES

Command Code (Hex)	Command Name	Read / Write	Page	# of Bytes	Bit #	Bit Name	Definition				Supported?
FB	BOOTLOAD_STATUS	R	All	2	0	BOOTLOADING_PRI	Set when primary uC bootloading in process				YES
					1	BOOTLOADING_FLOAT	Set when floating uC bootloading in process				YES
					2	BOOTLOADING_SEC	Set when secondary uC bootloading in process				YES
					3	BOOTLOADED_PRI	Set when primary uC bootloading completed; reset required				YES
					4	BOOTLOADED_FLOAT	Set when floating uC bootloading completed; reset required				YES
					5	BOOTLOADED_SEC	Set when secondary uC bootloading completed; reset required				YES
					6	RESET_PRI	Set when primary uC reset				YES
					7	RESET_FLOAT	Set when floating uC reset				YES
					8	RESET_SEC	Set when secondary uC reset				YES
					9	RESERVED					NO
					10	RESERVED					NO
					11	RESERVED					NO
					12	RESERVED					NO
					13	RESERVED					NO
					14	RESERVED					NO
					15	RESERVED					NO

The following tables represents typical results / responses returned from respective command code entries and is provided as an illustration of what should be expected.

#### RETURNED RESULTS, D1U54P-W-1500-12-HA3TC & D1U54P-W-1500-12-HA4TC

[Link back to: Commands](#)

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
40	VOUT_OV_FAULT_LIMIT	R	0	Linear Data Format	2	Vdc	-6				14		
40	VSTBY_OV_FAULT_LIMIT	R	1	Linear Data Format	2	Vdc	-7				6		
41	VOUT_OV_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
41	VSTBY_OV_FAULT_RESPONSE	R	1	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
42	VOUT_OV_WARN_LIMIT	R	0	Linear Data Format	2	Vdc	-6				13.1		
42	VSTBY_OV_WARN_LIMIT	R	1	Linear Data Format	2	Vdc	-7				5.4		
43	VOUT_UV_WARN_LIMIT	R	0	Linear Data Format	2	Vdc	-6				11.4		
43	VSTBY_UV_WARN_LIMIT	R	1	Linear Data Format	2	Vdc	-7				4.4		
44	VOUT_UV_FAULT_LIMIT	R	0	Linear Data Format	2	Vdc	-6				10.9		
44	VSTBY_UV_FAULT_LIMIT	R	1	Linear Data Format	2	Vdc	-7				4		
45	VOUT_UV_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
45	VSTBY_UV_FAULT_RESPONSE	R	1	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
46	IOUT_OC_FAULT_LIMIT	R	0	Linear Data Format	2	Adc	-2				140		
46	ISTBY_OC_FAULT_LIMIT	R	2	Linear Data Format	2	Adc	-7				5.5		
47	IOUT_OC_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	7	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Continuous restart (self-recovery)
47	ISTBY_OC_FAULT_RESPONSE	R	2	Bit Flags	1						2:0	0	Delay Time - None
											5:3	7	Response - Continuous restart (self-recovery)
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
4A	IOUT_OC_WARN_LIMIT	R	0	Linear Data Format	2	Adc	-2					133	
4A	ISTBY_OC_WARN_LIMIT	R	2	Linear Data Format	2	Adc	-7					5	
4F	AIRFLOW_1_OT_FAULT_LIMIT	R	0	Linear Data Format	2	°C	0					95	Primary Airflow - Outlet
4F	HOTSPOT_1_OT_FAULT_LIMIT	R	1	Linear Data Format	2	°C	0					120	Primary Hotspot - PFC
4F	AIRFLOW_2_OT_FAULT_LIMIT	R	2	Linear Data Format	2	°C	0					75	Secondary Airflow - Inlet
4F	HOTSPOT_2_OT_FAULT_LIMIT	R	3	Linear Data Format	2	°C	0					130	Secondary Hotspot - Main output hotspot
50	AIRFLOW_1_OT_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
50	HOTSPOT_1_OT_FAULT_RESPONSE	R	1	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
50	AIRFLOW_2_OT_FAULT_RESPONSE	R	2	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
50	HOTSPOT_2_OT_FAULT_RESPONSE	R	3	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
4F	AIRFLOW_1_OT_WARN_LIMIT	R	0	Linear Data Format	2	°C	0					85	Primary Airflow - Outlet

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
4F	HOTSPOT_1_OT_WARN_LIMIT	R	1	Linear Data Format	2	°C	0				110	Primary Hotspot - PFC	
4F	AIRFLOW_2_OT_WARN_LIMIT	R	2	Linear Data Format	2	°C	0				75	Secondary Airflow - Inlet	
4F	HOTSPOT_2_OT_WARN_LIMIT	R	3	Linear Data Format	2	°C	0				125	Secondary Hotspot - Main output hotspot	
55	VIN_OV_FAULT_LIMIT	R	0	Linear Data Format	2	Vrms	-1				280	Recoverable	
56	VIN_OV_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
57	VIN_OV_WARN_LIMIT	R	0	Linear Data Format	2	Vrms	-1				275	Recoverable	
58	VIN_UV_WARN_LIMIT	R	0	Linear Data Format	2	Vrms	-1				80	Recoverable	
59	VIN_UV_FAULT_LIMIT	R	0	Linear Data Format	2	Vrms	-1				70	Recoverable	
5A	VIN_UV_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
5B	IIN_OC_FAULT_LIMIT	R	0	Linear Data Format	2	Arms	-6				18		
5C	IIN_OC_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
5D	IIN_OC_WARN_LIMIT	R	0	Linear Data Format	2	Arms	-6				16.7		
5E	POWER_GOOD_ON	R	0	Linear Data Format	2	Vdc	-6				10.9		

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
5F	POWER_GOOD_OFF	R	0	Linear Data Format	2	Vdc	-6					10.9	
68	POUT_OP_FAULT_LIMIT	R	0	Linear Data Format	2	Watts	0					1660	
69	POUT_OP_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
6A	POUT_OP_WARN_LIMIT	R	0	Linear Data Format	2	Watts	0					1600	
6B	PIN_OP_WARN_LIMIT	R	0	Linear Data Format	2	Watts	0					1850	POUT_OP_WARN_LIMIT / 0.82

**RETURNED RESULTS, D1U54P-W-1500-12-HC3TC & D1U54P-W-1500-12-HC4TC**
[Link back to: Commands](#)

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
40	VOUT_OV_FAULT_LIMIT	R	0	Linear Data Format	2	Vdc	-6					14	
40	VSTBY_OV_FAULT_LIMIT	R	1	Linear Data Format	2	Vdc	-7					3.9	
41	VOUT_OV_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
41	VSTBY_OV_FAULT_RESPONSE	R	1	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
42	VOUT_OV_WARN_LIMIT	R	0	Linear Data Format	2	Vdc	-6					13.1	

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
42	VSTBY_OV_WARN_LIMIT	R	1	Linear Data Format	2	Vdc	-7				3.6		
43	VOUT_UV_WARN_LIMIT	R	0	Linear Data Format	2	Vdc	-6				11.4		
43	VSTBY_UV_WARN_LIMIT	R	1	Linear Data Format	2	Vdc	-7				3		
44	VOUT_UV_FAULT_LIMIT	R	0	Linear Data Format	2	Vdc	-6				10.9		
44	VSTBY_UV_FAULT_LIMIT	R	1	Linear Data Format	2	Vdc	-7				2.9		
45	VOUT_UV_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
45	VSTBY_UV_FAULT_RESPONSE	R	1	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
46	IOUT_OC_FAULT_LIMIT	R	0	Linear Data Format	2	Adc	-2				140		
46	ISTBY_OC_FAULT_LIMIT	R	2	Linear Data Format	2	Adc	-7				5.5		
47	IOUT_OC_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	7	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Continuous restart (self-recovery)	
47	ISTBY_OC_FAULT_RESPONSE	R	2	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	7	Response - Continuous restart (self-recovery)	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
4A	IOUT_OC_WARN_LIMIT	R	0	Linear Data Format	2	Adc	-2				133		

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
4A	ISTBY_OC_WARN_LIMIT	R	2	Linear Data Format	2	Adc	-7				5		
4F	AIRFLOW_1_OT_FAULT_LIMIT	R	0	Linear Data Format	2	°C	0				95	Primary Airflow - Outlet	
4F	HOTSPOT_1_OT_FAULT_LIMIT	R	1	Linear Data Format	2	°C	0				120	Primary Hotspot - PFC	
4F	AIRFLOW_2_OT_FAULT_LIMIT	R	2	Linear Data Format	2	°C	0				75	Secondary Airflow - Inlet	
4F	HOTSPOT_2_OT_FAULT_LIMIT	R	3	Linear Data Format	2	°C	0				130	Secondary Hotspot - Main output hotspot	
50	AIRFLOW_1_OT_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
50	HOTSPOT_1_OT_FAULT_RESPONSE	R	1	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
50	AIRFLOW_2_OT_FAULT_RESPONSE	R	2	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
50	HOTSPOT_2_OT_FAULT_RESPONSE	R	3	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
4F	AIRFLOW_1_OT_WARN_LIMIT	R	0	Linear Data Format	2	°C	0				85	Primary Airflow - Outlet	
4F	HOTSPOT_1_OT_WARN_LIMIT	R	1	Linear Data Format	2	°C	0				110	Primary Hotspot - PFC	

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
4F	AIRFLOW_2_OT_WARN_LIMIT	R	2	Linear Data Format	2	°C	0				70	Secondary Airflow - Inlet	
4F	HOTSPOT_2_OT_WARN_LIMIT	R	3	Linear Data Format	2	°C	0				125	Secondary Hotspot - Main output hotspot	
55	VIN_OV_FAULT_LIMIT	R	0	Linear Data Format	2	Vrms	-1				280	Recoverable	
56	VIN_OV_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
57	VIN_OV_WARN_LIMIT	R	0	Linear Data Format	2	Vrms	-1				275	Recoverable	
58	VIN_UV_WARN_LIMIT	R	0	Linear Data Format	2	Vrms	-1				80	Recoverable	
59	VIN_UV_FAULT_LIMIT	R	0	Linear Data Format	2	Vrms	-1				70	Recoverable	
5A	VIN_UV_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
5B	IIN_OC_FAULT_LIMIT	R	0	Linear Data Format	2	Arms	-6				18		
5C	IIN_OC_FAULT_RESPONSE	R	0	Bit Flags	1					2:0	0	Delay Time - None	
										5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear	
										7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared	
5D	IIN_OC_WARN_LIMIT	R	0	Linear Data Format	2	Arms	-6				16.7		
5E	POWER_GOOD_ON	R	0	Linear Data Format	2	Vdc	-6				10.9		
5F	POWER_GOOD_OFF	R	0	Linear Data Format	2	Vdc	-6				10.9		

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
68	POUT_OP_FAULT_LIMIT	R	0	Linear Data Format	2	Watts	0					1660	
69	POUT_OP_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
6A	POUT_OP_WARN_LIMIT	R	0	Linear Data Format	2	Watts	0					1600	
6B	PIN_OP_WARN_LIMIT	R	0	Linear Data Format	2	Watts	0					1850	POUT_OP_WARN_LIMIT / 0.82

**RETURNED RESULTS, D1U54P-W-1500-12-HB4TC**
**Link back to: [Commands](#)**

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
40	VOUT_OV_FAULT_LIMIT	R	0	Linear Data Format	2	Vdc	-6					14	
40	VSTBY_OV_FAULT_LIMIT	R	1	Linear Data Format	2	Vdc	-7					14	
41	VOUT_OV_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
41	VSTBY_OV_FAULT_RESPONSE	R	1	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
42	VOUT_OV_WARN_LIMIT	R	0	Linear Data Format	2	Vdc	-6					13.1	
42	VSTBY_OV_WARN_LIMIT	R	1	Linear Data Format	2	Vdc	-7					13.5	
43	VOUT_UV_WARN_LIMIT	R	0	Linear Data Format	2	Vdc	-6					11.4	

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
43	VSTBY_UV_WARN_LIMIT	R	1	Linear Data Format	2	Vdc	-7					11.3	
44	VOUT_UV_FAULT_LIMIT	R	0	Linear Data Format	2	Vdc	-6					10.9	
44	VSTBY_UV_FAULT_LIMIT	R	1	Linear Data Format	2	Vdc	-7					11.1	
45	VOUT_UV_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
45	VSTBY_UV_FAULT_RESPONSE	R	1	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
46	IOUT_OC_FAULT_LIMIT	R	0	Linear Data Format	2	Adc	-2					140	
46	ISTBY_OC_FAULT_LIMIT	R	2	Linear Data Format	2	Adc	-7					3	
47	IOUT_OC_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	7	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Continuous restart (self-recovery)
47	ISTBY_OC_FAULT_RESPONSE	R	2	Bit Flags	1						2:0	0	Delay Time - None
											5:3	7	Response - Continuous restart (self-recovery)
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
4A	IOUT_OC_WARN_LIMIT	R	0	Linear Data Format	2	Adc	-2					133	
4A	ISTBY_OC_WARN_LIMIT	R	2	Linear Data Format	2	Adc	-7					2.7	
4F	AIRFLOW_1_OT_FAULT_LIMIT	R	0	Linear Data Format	2	°C	0					95	Primary Airflow - Outlet

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
4F	HOTSPOT_1_OT_FAULT_LIMIT	R	1	Linear Data Format	2	°C	0				120	Primary Hotspot - PFC	
4F	AIRFLOW_2_OT_FAULT_LIMIT	R	2	Linear Data Format	2	°C	0				75	Secondary Airflow - Inlet	
4F	HOTSPOT_2_OT_FAULT_LIMIT	R	3	Linear Data Format	2	°C	0				130	Secondary Hotspot - Main output hotspot	
50	AIRFLOW_1_OT_FAULT_RESPONSE	R	0	Bit Flags	1		2:0	0	Delay Time - None		5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
50	HOTSPOT_1_OT_FAULT_RESPONSE	R	1	Bit Flags	1		2:0	0	Delay Time - None		5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
50	AIRFLOW_2_OT_FAULT_RESPONSE	R	2	Bit Flags	1		2:0	0	Delay Time - None		5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
50	HOTSPOT_2_OT_FAULT_RESPONSE	R	3	Bit Flags	1		2:0	0	Delay Time - None		5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
4F	AIRFLOW_1_OT_WARN_LIMIT	R	0	Linear Data Format	2	°C	0				85	Primary Airflow - Outlet	
4F	HOTSPOT_1_OT_WARN_LIMIT	R	1	Linear Data Format	2	°C	0				110	Primary Hotspot - PFC	
4F	AIRFLOW_2_OT_WARN_LIMIT	R	2	Linear Data Format	2	°C	0				70	Secondary Airflow - Inlet	
4F	HOTSPOT_2_OT_WARN_LIMIT	R	3	Linear Data Format	2	°C	0				125	Secondary Hotspot - Main output hotspot	

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
55	VIN_OV_FAULT_LIMIT	R	0	Linear Data Format	2	Vrms	-1					280	Recoverable
56	VIN_OV_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
57	VIN_OV_WARN_LIMIT	R	0	Linear Data Format	2	Vrms	-1					275	Recoverable
58	VIN_UV_WARN_LIMIT	R	0	Linear Data Format	2	Vrms	-1					80	Recoverable
59	VIN_UV_FAULT_LIMIT	R	0	Linear Data Format	2	Vrms	-1					70	Recoverable
5A	VIN_UV_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
5B	IIN_OC_FAULT_LIMIT	R	0	Linear Data Format	2	Arms	-6					18	
5C	IIN_OC_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
5D	IIN_OC_WARN_LIMIT	R	0	Linear Data Format	2	Arms	-6					16.7	
5E	POWER_GOOD_ON	R	0	Linear Data Format	2	Vdc	-6					10.9	
5F	POWER_GOOD_OFF	R	0	Linear Data Format	2	Vdc	-6					10.9	
68	POUT_OP_FAULT_LIMIT	R	0	Linear Data Format	2	Watts	0					1660	

Command Code (Hex)	Command Name	Read / Write	Page	Format	# of Bytes	Units	Scaling Coefficients				Bit #	Reading	Comments
							N	m	R	b			
69	POUT_OP_FAULT_RESPONSE	R	0	Bit Flags	1						2:0	0	Delay Time - None
											5:3	0	Retry Setting - Unit does not attempt to restart & output remains disabled until fault clear
											7:6	3	Response - Output disabled while fault is present & remains disabled until fault cleared
6A	POUT_OP_WARN_LIMIT	R	0	Linear Data Format	2	Watts	0					1600	
6B	PIN_OP_WARN_LIMIT	R	0	Linear Data Format	2	Watts	0					1850	POUT_OP_WARN_LIMIT / 0.82

**SENSOR DATA AND RESOLUTION: D1U54P-W-1500-12-HA4TC**
[Link Back to: Command 88](#)

Command Code (Hex)	Command Name	Description	Page	Format	Units	Scaling Coefficients				Raw Sensor		PMBus Reporting Sensor		
						N	m	R	b	Full-scale / Range	Resolution	Full-scale / Range	Resolution	Accuracy
88	READ_VIN	Input Voltage Sensor Reading	All	Linear Data Format	Vrms	-1				327.93	0.3206	511.5	0.5	+ / - 5% of Reporting Full-Scale
89	READ_IIN	Input Current Sensor Reading	All	Linear Data Format	Arms	-5				17.86	0.0175	31.97	0.0313	+ / - 5% of Reporting Full-Scale
8B	READ_VOUT	Main Output Voltage Sensor Reading	0	Linear Data Format	Vdc	-6				14.79	0.0145	15.98	0.0156	+ / - 5% of Reporting Full-Scale
8B	READ_VSTBY	Standby(Auxiliary) Output Voltage Sensor Reading	1	Linear Data Format	Vdc	-7				6.6	0.0065	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8C	READ_IOUT	Main Output Current Sensor Reading	0	Linear Data Format	Adc	-2				173.65	0.1697	255.75	0.250	+ / - 5% of Reporting Full-Scale
8C	READ_ISTBY	Standby(Auxiliary) Output Current Sensor Reading	1	Linear Data Format	Adc	-7				4.33	0.0042	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8D	READ_TEMPERATURE_1	Temperature Sensor Reading - Inlet (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8E	READ_TEMPERATURE_2	Temperature Sensor Reading - Outlet (Primary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - Main Output Hotspot (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - PFC Hotspot (Primary Side)	1	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
90	READ_FAN_SPEED_1	Fan 1 Speed Sensor Reading	All	Linear Data Format	RPM	5				24,000		32736	32	+ / - 5% of Reporting Full-Scale or +/- 3520, 8% manufacturer speed tolerance
96	READ_POUT	Output Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
97	READ_PIN	Input Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
E2	READ_POWER_ON_HOURS	Accumulated Main Output Power-On Hours	All	Linear Data Format	Hours	0				~1,900 (Years)		~1,900 (Years)	1	+ / - 3%

**SENSOR DATA AND RESOLUTION: D1U54P-W-1500-12-HA3TC**
**Link to Commands: [Command back 88](#)**

Command Code (Hex)	Command Name	Description	Page	Format	Units	Scaling Coefficients				Raw Sensor		PMBus Reporting Sensor		
						N	m	R	b	Full-scale / Range	Resolution	Full-scale / Range	Resolution	Accuracy
88	READ_VIN	Input Voltage Sensor Reading	All	Linear Data Format	Vrms	-1				327.93	0.3206	511.5	0.5	+ / - 5% of Reporting Full-Scale
89	READ_IIN	Input Current Sensor Reading	All	Linear Data Format	Arms	-5				17.86	0.0175	31.97	0.0313	+ / - 5% of Reporting Full-Scale
8B	READ_VOUT	Main Output Voltage Sensor Reading	0	Linear Data Format	Vdc	-6				14.79	0.0145	15.98	0.0156	+ / - 5% of Reporting Full-Scale
8B	READ_VSTBY	Standby(Auxiliary) Output Voltage Sensor Reading	1	Linear Data Format	Vdc	-7				6.6	0.0065	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8C	READ_IOUT	Main Output Current Sensor Reading	0	Linear Data Format	Adc	-2				173.65	0.1697	255.75	0.250	+ / - 5% of Reporting Full-Scale
8C	READ_ISTBY	Standby(Auxiliary) Output Current Sensor Reading	1	Linear Data Format	Adc	-7				4.33	0.0042	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8D	READ_TEMPERATURE_1	Temperature Sensor Reading - Inlet (Primary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8E	READ_TEMPERATURE_2	Temperature Sensor Reading - Outlet (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - Main Output Hotspot (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - PFC Hotspot (Primary Side)	1	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
90	READ_FAN_SPEED_1	Fan 1 Speed Sensor Reading	All	Linear Data Format	RPM	5				24,000		32736	32	+ / - 5% of Reporting Full-Scale or +/- 3520, 8% manufacturer speed tolerance
96	READ_POUT	Output Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
97	READ_PIN	Input Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
E2	READ_POWER_ON_HOURS	Accumulated Main Output Power-On Hours	All	Linear Data Format	Hours	0				~1,900 (Years)		~1,900 (Years)	1	+ / - 3%

**SENSOR DATA AND RESOLUTION: D1U54P-W-1500-12-HB4TC**
**Link to Commands: [Command back 88](#)**

Command Code (Hex)	Command Name	Description	Page	Format	Units	Scaling Coefficients				Raw Sensor		PMBus Reporting Sensor		
						N	m	R	b	Full-scale / Range	Resolution	Full-scale / Range	Resolution	Accuracy
88	READ_VIN	Input Voltage Sensor Reading	All	Linear Data Format	Vrms	-1				327.93	0.3206	511.5	0.5	+ / - 5% of Reporting Full-Scale
89	READ_IIN	Input Current Sensor Reading	All	Linear Data Format	Arms	-5				17.86	0.0175	31.97	0.0313	+ / - 5% of Reporting Full-Scale
8B	READ_VOUT	Main Output Voltage Sensor Reading	0	Linear Data Format	Vdc	-6				14.79	0.0145	15.98	0.0156	+ / - 5% of Reporting Full-Scale
8B	READ_VSTBY	Standby(Auxiliary) Output Voltage Sensor Reading	1	Linear Data Format	Vdc	-6				14.73	0.0144	15.984	0.01563	+ / - 5% of Reporting Full-Scale
8C	READ_IOUT	Main Output Current Sensor Reading	0	Linear Data Format	Adc	-2				173.65	0.1697	255.75	0.250	+ / - 5% of Reporting Full-Scale
8C	READ_ISTBY	Standby(Auxiliary) Output Current Sensor Reading	1	Linear Data Format	Adc	-8				4.33	0.0042	3.996	0.00391	+ / - 5% of Reporting Full-Scale
8D	READ_TEMPERATURE_1	Temperature Sensor Reading - Inlet (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8E	READ_TEMPERATURE_2	Temperature Sensor Reading - Outlet (Primary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - Main Output Hotspot (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - PFC Hotspot (Primary Side)	1	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
90	READ_FAN_SPEED_1	Fan 1 Speed Sensor Reading	All	Linear Data Format	RPM	5				24,000		32736	32	+ / - 5% of Reporting Full-Scale or +/- 3520, 8% manufacturer speed tolerance
96	READ_POUT	Output Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
97	READ_PIN	Input Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
E2	READ_POWER_ON_HOURS	Accumulated Main Output Power-On Hours	All	Linear Data Format	Hours	0				~1,900 (Years)		~1,900 (Years)	1	+ / - 3%

**SENSOR DATA AND RESOLUTION: D1U54P-W-1500-12-HC4TC**
[Link to Commands: Command back 88](#)

Command Code (Hex)	Command Name	Description	Page	Format	Units	Scaling Coefficients				Raw Sensor		PMBus Reporting Sensor		
						N	m	R	b	Full-scale / Range	Resolution	Full-scale / Range	Resolution	Accuracy
88	READ_VIN	Input Voltage Sensor Reading	All	Linear Data Format	Vrms	-1				327.93	0.3206	511.5	0.5	+ / - 5% of Reporting Full-Scale
89	READ_IIN	Input Current Sensor Reading	All	Linear Data Format	Arms	-5				17.86	0.0175	31.97	0.0313	+ / - 5% of Reporting Full-Scale
8B	READ_VOUT	Main Output Voltage Sensor Reading	0	Linear Data Format	Vdc	-6				14.79	0.0145	15.98	0.0156	+ / - 5% of Reporting Full-Scale
8B	READ_VSTBY	Standby(Auxiliary) Output Voltage Sensor Reading	1	Linear Data Format	Vdc	-7				6.6	0.0065	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8C	READ_IOUT	Main Output Current Sensor Reading	0	Linear Data Format	Adc	-2				173.65	0.1697	255.75	0.250	+ / - 5% of Reporting Full-Scale
8C	READ_ISTBY	Standby(Auxiliary) Output Current Sensor Reading	1	Linear Data Format	Adc	-7				4.33	0.0042	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8D	READ_TEMPERATURE_1	Temperature Sensor Reading - Inlet (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8E	READ_TEMPERATURE_2	Temperature Sensor Reading - Outlet (Primary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - Main Output Hotspot (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - PFC Hotspot (Primary Side)	1	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
90	READ_FAN_SPEED_1	Fan 1 Speed Sensor Reading	All	Linear Data Format	RPM	5				24,000		32736	32	+ / - 5% of Reporting Full-Scale or +/- 3520, 8% manufacturer speed tolerance
96	READ_POUT	Output Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
97	READ_PIN	Input Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
E2	READ_POWER_ON_HOURS	Accumulated Main Output Power-On Hours	All	Linear Data Format	Hours	0				~1,900 (Years)		~1,900 (Years)	1	+ / - 3%

**SENSOR DATA AND RESOLUTION: D1U54P-W-1500-12-HC3TC**
**Link back to Commands: [Command back 88](#)**

Command Code (Hex)	Command Name	Description	Page	Format	Units	Scaling Coefficients				Raw Sensor		PMBus Reporting Sensor		
						N	m	R	b	Full-scale / Range	Resolution	Full-scale / Range	Resolution	Accuracy
88	READ_VIN	Input Voltage Sensor Reading	All	Linear Data Format	Vrms	-1				327.93	0.3206	511.5	0.5	+ / - 5% of Reporting Full-Scale
89	READ_IIN	Input Current Sensor Reading	All	Linear Data Format	Arms	-5				17.86	0.0175	31.97	0.0313	+ / - 5% of Reporting Full-Scale
8B	READ_VOUT	Main Output Voltage Sensor Reading	0	Linear Data Format	Vdc	-6				14.79	0.0145	15.98	0.0156	+ / - 5% of Reporting Full-Scale
8B	READ_VSTBY	Standby(Auxiliary) Output Voltage Sensor Reading	1	Linear Data Format	Vdc	-7				6.6	0.0065	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8C	READ_IOUT	Main Output Current Sensor Reading	0	Linear Data Format	Adc	-2				173.65	0.1697	255.75	0.250	+ / - 5% of Reporting Full-Scale
8C	READ_ISTBY	Standby(Auxiliary) Output Current Sensor Reading	1	Linear Data Format	Adc	-7				4.33	0.0042	7.992	0.00781	+ / - 5% of Reporting Full-Scale
8D	READ_TEMPERATURE_1	Temperature Sensor Reading - Inlet (Primary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8E	READ_TEMPERATURE_2	Temperature Sensor Reading - Outlet (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - Main Output Hotspot (Secondary Side)	0	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
8F	READ_TEMPERATURE_3	Temperature Sensor Reading - PFC Hotspot (Primary Side)	1	Linear Data Format	°C	0				-40 to 150		-40 to 150	1	+ / - 5°C
90	READ_FAN_SPEED_1	Fan 1 Speed Sensor Reading	All	Linear Data Format	RPM	5				24,000		32736	32	+ / - 5% of Reporting Full-Scale or +/- 3520, 8% manufacturer speed tolerance
96	READ_POUT	Output Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
97	READ_PIN	Input Power Sensor Reading	All	Linear Data Format	Watts	1						2046	2	+ / - 5% of Reporting Full-Scale
E2	READ_POWER_ON_HOURS	Accumulated Main Output Power-On Hours	All	Linear Data Format	Hours	0				~1,900 (Years)		~1,900 (Years)	1	+ / - 3%

**MANUFACTURER'S GENERAL PARAMETRIC DATA**
[Link back to: Command Back A1](#)

Command Code (Hex)	Command Name	Value (Real World)	Units	N	Value (dec)
A0	MFR_VIN_MIN	90	V	-1	180
A1	MFR_VIN_MAX	264	V	-1	528
A2	MFR_IIN_MAX	15	A	-5	480
A3	MFR_PIN_MAX	1800	W	1	900
A4	MFR_VOUT_MIN	11.7	V	-6	749
A5	MFR_VOUT_MAX	12.3	V	-6	787
A6	MFR_IOUT_MAX	125	A	-2	500
A7	MFR_POUT_MAX	1500	W	1	750
A8	MFR_TAMBIENT_MAX	50	C	0	50
A9	MFR_TAMBIENT_MIN	0	C	0	0
AA	MFR EFFICIENCY_LL_VIN	0	V	-1	0
	MFR EFFICIENCY_LL_POUT1	0	W	1	0
	MFR EFFICIENCY_LL_EFF1	0		-10	0
	MFR EFFICIENCY_LL_POUT2	0	W	1	0
	MFR EFFICIENCY_LL_EFF2	0		-10	0
	MFR EFFICIENCY_LL_POUT3	0	W	1	0
	MFR EFFICIENCY_LL_EFF3	0		-10	0
AB	MFR EFFICIENCY_HL_VIN	230	V	-1	460
	MFR EFFICIENCY_HL_POUT1	300	W	1	150
	MFR EFFICIENCY_HL_EFF1	0.9		-10	922
	MFR EFFICIENCY_HL_POUT2	750	W	1	375
	MFR EFFICIENCY_HL_EFF2	0.94		-10	963
	MFR EFFICIENCY_HL_POUT3	1500	W	1	750
	MFR EFFICIENCY_HL_EFF3	0.91		-10	932

**OPERATION COMMAND CODE 01 HEX**

Link Back to Commands: [back to command 01](#)

Bit # / Bit Description									Valid Values		Power Supply On/Off Mode
7	6	5	4	3	2	1	0		Dec	Hex	
On/off 1	On/off 0	Margin on/off/high/low 1	Margin on/off/high/low 0	Margin fault control 1	Margin fault control 0	not used	not used				
0	0	x	x	x	x	x	x	0 - 63	0 - 3F	Disable power supply when OPERATION command supported	
1	0	x	x	x	x	x	x	128 - 191	80 - BF	Enable power supply when OPERATION command supported (Default)	

**ON/OFF COMMAND CODE 02 HEX**

Link Back to Commands: [back to command 02](#)

Bit # / Bit Description								Valid Values		Power Supply On/Off Mode	
7	6	5	4	3	2	1	0		Dec	Hex	
reserved	reserved	reserved	CONTROL pin / OPERATION command PS on/off	OPERATION command on/off	CONTROL pin on/off	CONTROL pin polarity	CONTROL pin action				
0	0	0	1	0	1	0	1	21	15	Control pin only ; active low polarity	
0	0	0	1	0	1	1	1	23	17	Control pin only ; active high polarity	
0	0	0	1	1	0	x	1	25 or 27	19 or 1B	Operation command only	
0	0	0	1	1	1	0	1	29	1D	Operation command and control pin ; active low polarity (Default)	
0	0	0	1	1	1	1	1	31	1F	Operation command and control pin ; active high polarity	

**EEPROM DATA: Example, based on D1U54P-W-1500-12-HC4TC. Actual results may vary based on model**
**Link back to: Command\_E1**

Address	Data Length	Register Contents (Hexadecimal Format) Order = Low Address -> High Address Dynamic Data Byte = "xx"	Register Name	Static or Dynamic Register? (S/D)	Data Type	Description
0x00	1	01	IPMI common header	S	HEX	
0x01	1	00		S	HEX	
0x02	1	00		S	HEX	
0x03	1	00		S	HEX	
0x04	1	01		S	HEX	
0x05	1	00		S	HEX	
0x06	1	00		S	HEX	
0x07	1	FE		S	HEX	
0x08	1	01		S	HEX	
0x09	1	09		S	HEX	
0xA	1	19	Product area - language code	S	HEX	
0xB	1	C9	Manufacturer name - length	S	HEX	
0xC - 0x14	9	4D,75,72,61,74,61,2D,50,53	Manufacturer name	S	TEXT	Murata-PS
0x15	1	C5	Product name - length	S	HEX	
0x16 - 0x1A	5	4D,31,38,39,31	Product name	S	TEXT	M1891
0x1B	1	D9	Product part/model number - length	S	HEX	
0x1C - 0x31	22	44,31,55,35,34,50,2D,57,2D,31,35,30,30,2D,3 1,32,2D,48,43,34,54,43	Product part/model number	S	TEXT	D1U54P-W-1500-12-HC4TC
0x32	1	C0	Product version - unused	S	HEX	
0x33	1	CC	Serial number - length	S	HEX	
0x34- 0x3F	12	xx,xx,xx,xx,xx,xx,xx,xx,xx,xx,xx,xx	Serial number	D	TEXT	
0x40 - 0x45	6	C0,C0,C0,C0,C0,C0	Unused product area fields	S	HEX	
0x46	1	C1	End of product area data	S	HEX	
0x47 - 0x4B	5	00	Pad	D	HEX	Fill unused space
0x4C	1	xx	Product area checksum	D	HEX	0x08 - 0x4B - Twos complement
0x4D - 0xFF	179	00	Pad	S	HEX	Fill unused space

### PMBUS Configuration Bits

**Link back to: Command\_EE**

Parameter	Bit#	Bit	Function	
Data Format	Bit 0	1	Direct Data Format	
		0	Linear Data Format	Default
SMBALERT	Bit 1	1	PS does not have SMBALERT pin or does not support SMBus alert protocol	
		0	PS does have SMBALERT pin and supports SMBus alert protocol	Default
Bus Speed	Bit 2	1	Maximum supported bus speed = 400kHz	Default
		0	Maximum supported bus speed = 100kHz	
PEC support	Bit 3	1	Packed error checking supported	Default
		0	Packed error checking not supported	

**LED CONTROL**

Link back to commands: [Command\\_EF](#)

Bit # / Bit Description								Valid Values		Read / Write	LED Status & Control	
7	6	5	4	3	2	1	0	Dec	Hex			
CONTROL Bit	reserved	reserved	reserved	reserved	LED Mode Bit 2	LED Mode Bit 1	LED Mode Bit 0					
<b>Page 0 - INPUT LED</b>												
0	0	0	0	0	0	0	0	0	0	Read	Auto - LED off (default)	
0	0	0	0	0	0	0	1	1	1	Read	Auto - LED solid green (default)	
0	0	0	0	0	0	1	0	2	2	Read	Auto - LED blinking green (default)	
0	X	X	X	X	X	X	X	0 - 127	0 - 7F	Write	Set to Auto LED control	
1	0	0	0	0	0	0	0	128	80	Read / Write	Set to Manual - LED off	
1	0	0	0	0	0	0	1	129	81	Read / Write	Set to Manual - LED solid green	
1	0	0	0	0	0	1	0	130	82	Read / Write	Set to Manual - LED blinking green	
<b>Page 1 - OUTPUT LED</b>												
0	0	0	0	0	0	0	0	0	0	Read	Auto - LED off (default)	
0	0	0	0	0	0	0	1	1	1	Read	Auto - LED solid green (default)	
0	0	0	0	0	0	1	0	2	2	Read	Auto - LED blinking green (default)	
0	0	0	0	0	0	1	1	3	3	Read	Auto - LED solid red (default)	
0	0	0	0	0	1	0	0	4	4	Read	Auto - LED blinking red (default)	
0	0	0	0	0	1	0	1	5	5	Read	Auto - LED solid yellow (default)	
0	0	0	0	0	1	1	0	6	6	Read	Auto - LED blinking yellow (default)	
0	X	X	X	X	X	X	X	0 - 127	0 - 7F	Write	Set to Auto LED control	
1	0	0	0	0	0	0	0	128	80	Read / Write	Set to Manual - LED off	
1	0	0	0	0	0	0	1	129	81	Read / Write	Set to Manual - LED solid green	
1	0	0	0	0	0	1	0	130	82	Read / Write	Set to Manual - LED blinking green	
1	0	0	0	0	0	1	1	131	83	Read / Write	Set to Manual - LED solid red	
1	0	0	0	0	0	1	0	132	84	Read / Write	Set to Manual - LED blinking red	
1	0	0	0	0	0	1	0	133	85	Read / Write	Set to Manual - LED solid yellow	
1	0	0	0	0	0	1	1	0	134	86	Read / Write	Set to Manual - LED blinking yellow

= Default, x=don't care

**Manufacturers Vital Data**

Command Code 99 HEX (MAN\_ID)

Link back to commands: [Command\\_Back\\_99](#)

Command Code (Hex)	Command Name	Value	ID Length/Bit#/ID/ASCII Text		
99	MFR_ID	Murata-PS	MFR_ID_LENGTH:	9	
			MFR_ID_0		'M'
			MFR_ID_1		'u'
			MFR_ID_2		'r'
			MFR_ID_3		'a'
			MFR_ID_4		't'
			MFR_ID_5		'a'
			MFR_ID_6		'-'
			MFR_ID_7		'P'
			MFR_ID_8		'S'

Command Code 9A HEX (MFR\_MODEL), D1U54P-W-1500-12-HA4TC shown for example purposes:

[www.murata-ps.com/support](http://www.murata-ps.com/support)

Link back to commands: [Command Back 9A](#)

Command Code (Hex)	Command Name	Value	ID Length/Bit#/ID/ASCII Text		
9A	MFR_MODEL	D1U54P-W-1500-12-HA4TC	MFR_MODEL_LENGTH	22	
			MFR_MODEL_0		'D'
			MFR_MODEL_1		'1'
			MFR_MODEL_2		'U'
			MFR_MODEL_3		'5'
			MFR_MODEL_4		'4'
			MFR_MODEL_5		'P'
			MFR_MODEL_6		'_'
			MFR_MODEL_7		'W'
			MFR_MODEL_8		'_'
			MFR_MODEL_9		'1'
			MFR_MODEL_10	'5'	
			MFR_MODEL_11	'0'	
			MFR_MODEL_12	'0'	
			MFR_MODEL_13	'_'	
			MFR_MODEL_14	'1'	
			MFR_MODEL_15	'2'	
			MFR_MODEL_16	'_'	
			MFR_MODEL_17	'H'	
			MFR_MODEL_18	'A'	
			MFR_MODEL_19	'4'	
			MFR_MODEL_20	'T'	
			MFR_MODEL_21	'C'	
			MFR_MODEL_22	0	
			MFR_MODEL_23	0	
			MFR_MODEL_24	0	
			MFR_MODEL_25	0	
			MFR_MODEL_26	0	
			MFR_MODEL_27	0	
			MFR_MODEL_28	0	

Command Code 9B HEX (MFR\_REVISION), example only; actual results may vary:

Link Back to Commands: [Command 9B](#)

Command Code (Hex)	Command Name	Value	ID Length/Bit#/ID/ASCII Text		
9B	MFR_REVISION	0000-0000-0000	MFR_REVISION_LENGTH	14	
			MFR_REVISION_0	'0'	
			MFR_REVISION_1	'0'	
			MFR_REVISION_2	'0'	
			MFR_REVISION_3	'0'	
			MFR_REVISION_4	'_'	
			MFR_REVISION_5	SEC_MAJOR_FW_REV_0	// Secondary FW major rev byte0
			MFR_REVISION_6	SEC_MAJOR_FW_REV_1	// Secondary FW major rev byte1
			MFR_REVISION_7	SEC_MINOR_FW_REV_0	// Secondary FW minor rev byte0
			MFR_REVISION_8	SEC_MINOR_FW_REV_1	// Secondary FW minor rev byte1
			MFR_REVISION_9	'_'	
			MFR_REVISION_10	'0'	
			MFR_REVISION_11	'0'	
			MFR_REVISION_12	'0'	
			MFR_REVISION_13	'0'	

Command Code 9C HEX (MFR\_LOCATION):

[www.murata-ps.com/support](http://www.murata-ps.com/support)

Link Back to Commands List: [Command\\_Back\\_9C](#)

Command Code (Hex)	Command Name	Value	ID Length/Bit#ID/ASCII Text
9C	MFR_LOCATION	China	MFR_LOCATION_LENGTH
			MFR_LOCATION_0
			'C'
			MFR_LOCATION_1
			'h'
			'i'
9D	MFR_DATE	1400	MFR_LOCATION_3
			'n'
			MFR_LOCATION_4
			'a'

Command Code 9D HEX (MFR\_DATE) example only; actual results may very::

Link Back to Commands List: [Command\\_Back\\_9D](#)

Command Code (Hex)	Command Name	Value	ID Length/Bit#ID/ASCII Text
9D	MFR_DATE	1400	MFR_LOCATION_LENGTH
			'1'
			MFR_DATE_0
			"4"
			MFR_DATE_1
			"0"
9E	MFR_SERIAL	QEyywwR1xxxx	MFR_DATE_2
			"0"
			MFR_DATE_3

Command Code 9E HEX (MFR\_SERIAL) example only; actual unit results may very:

Link Back to Commands List: [Command\\_Back\\_9E](#)

Command Code (Hex)	Command Name	Value	ID Length/Bit#ID/ASCII Text
9E	MFR_SERIAL	QEyywwR1xxxx	MFR_SERIAL_LENGTH
			'Q'
			MFR_SERIAL_0
			'E'
			MFR_SERIAL_1
			'y'
			MFR_SERIAL_2
			'y'
			MFR_SERIAL_3
			'w'
			MFR_SERIAL_4
			'w'
9F	MFR_FAN	1000000000000000	MFR_SERIAL_5
			'R'
			MFR_SERIAL_6
			'1'
			MFR_SERIAL_7
			'x'
			MFR_SERIAL_8
			'x'
9F	MFR_FAN	1000000000000000	MFR_SERIAL_9
			'x'
			MFR_SERIAL_10
			'x'
9F	MFR_FAN	1000000000000000	MFR_SERIAL_11
			'x'

Command Code **3Bh** (FAN\_COMMAND\_1) Link Back to Commands List: [COMMAND\\_3B](#)

Manual fan speed control via PMBus is a linear data mode two byte command, speed expressed as a percentage of the maximum fan duty cycle.

Automatic fan speed control (default) can be resumed by writing the command “03h”, (CLEAR\_FAULTS). This table contains the manual fan speed command data in 1% increments, for illustration purposes:

CMD 3B(h)	“Fan_COMMAND_1” (2 bytes)			CMD 3B(h)	“Fan_COMMAND_1” (2 bytes)			CMD 3B(h)	“Fan_COMMAND_1” (2 bytes)			CMD 3B(h)	“Fan_COMMAND_1” (2 bytes)		
% Duty Cycle	MSB(h)	LSB(h)	n(d)	% Duty Cycle	MSB(h)	LSB(h)	n(d)	% Duty Cycle	MSB(h)	LSB(h)	n(d)	% Duty Cycle	MSB(h)	LSB(h)	n(d)
0	B0	0	-10	26	B1	A	-10	51	B2	A	-10	76	B2	9	-10
1	B0	A	-10	27	B1	14	-10	52	B2	14	-10	77	B2	14	-10
2	B0	14	-10	28	B1	E1	-10	53	B2	1E	-10	78	B2	1E	-10
3	B0	1F	-10	29	B1	29	-10	54	B2	28	-10	79	B2	28	-10
4	B0	29	-10	30	B1	33	-10	55	B2	33	-10	80	B3	32	-10
5	B0	33	-10	31	B1	3D	-10	56	B2	3D	-10	81	B3	3D	-10
6	B0	3D	-10	32	B1	47	-10	57	B2	47	-10	82	B3	47	-10
7	B0	48	-10	33	B1	52	-10	58	B2	51	-10	83	B3	51	-10
8	B0	52	-10	34	B1	5C	-10	59	B2	5C	-10	84	B3	5B	-10
9	B0	5C	-10	35	B1	66	-10	60	B2	66	-10	85	B3	66	-10
10	B0	66	-10	36	B1	70	-10	61	B2	70	-10	86	B3	70	-10
11	B0	71	-10	37	B1	7B	-10	62	B2	7A	-10	87	B3	7A	-10
12	B0	7B	-10	38	B1	85	-10	63	B2	84	-10	88	B3	84	-10
13	B0	85	-10	39	B1	8F	-10	64	B2	8F	-10	89	B3	8E	-10
14	B0	8F	-10	40	B1	99	-10	65	B2	99	-10	90	B3	99	-10
15	B0	99	-10	41	B1	A3	-10	66	B2	A3	-10	91	B3	A3	-10
16	B0	A4	-10	42	B1	AE	-10	67	B2	AD	-10	92	B3	AD	-10
17	B0	AE	-10	43	B1	B8	-10	68	B2	B8	-10	93	B3	B7	-10
18	B0	B8	-10	44	B1	C2	-10	9	B2	C2	-10	94	B3	C2	-10
19	B0	C2	-10	45	B1	CC	-10	70	B2	CC	-10	95	B3	CC	-10
20	B0	CD	-10	46	B1	D7	-10	71	B2	D6	-10	96	B3	D6	-10
21	B0	D7	-10	47	B1	E1	-10	72	B2	E1	-10	97	B3	E0	-10
22	B0	E1	-10	48	B1	EB	-10	73	B2	EB	-10	98	B3	EB	-10
23	B0	EB	-10	49	B1	F5	-10	74	B2	F5	-10	99	B3	F5	-10
24	B0	F6	-10	50	B2	0	-10	75	B2	FF	-10	100	B3	FF	-10
25	B1	0	-10												

Murata Power Solutions, Inc.  
 11 Cabot Boulevard, Mansfield, MA 02048 -1151 U.S.A.  
 ISO 9001 and 14001 REGISTERED



This product is subject to the following operating requirements  
 and the Life and Safety Critical Application Sales Policy:  
 Refer to: <http://www.murata-ps.com/requirements/>

Murata Power Solutions, Inc. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The descriptions contained herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice.

© 2016 Murata Power Solutions, Inc.